

MP602 Conversion Lead 12N / 12S Plugs to 13 Pin Socket					
This conversion lead is wired to the following table					
Please check compatability with your vehicle and caravan					
The Contact Allocations Shown Are To The Quoted International Standards					
I.S.O. 1724			I.S.O. 11446		
7 Pin 12N Plug			13 Pin Socket		
Contact Number	FUNCTION	CONNECTION	Contact Number	FUNCTION	
1	L / H Indicator	Connected To	1	L / H Indicator	
2	Rear Fog Lamps	Connected To	2	Rear Fog Lamps	
3	Earth Return	Connected To	3	Earth Return	
4	R/H Indicator	Connected To	4	R / H Indicator	
5	R / H Tail & No. Plate	Connected To	5	R / H Tail & No. Plate	
6	Stop Lamps	Connected To	6	Stop Lamps	
7	L / H Tail & No. Plate	Connected To	7	L / H Tail & No. Plate	
I.S.O. 3732					
7 Pin 12S Plug					
1	Reversing Lamps	Connected To	8	Reversing Lamps	
2	No Allocation	Not Wired	12	No Allocation	
3	Earth Return (contact 4)	Connected To	13	Earth Return (for contact 9)	
4	Power Supply Steady	Connected To	9	Power Supply Steady	
5	No Allocation	Not Wired			
6	Power Supply Switched	Connected To	10	Power Supply Switched (fridge)	
7	Earth Return (contact 6)	Connected To	11	Earth Return (for contact 10)	